

# Cync No Neutral Required Switches Specifications



## Device

Switch Image					
<b>Switch Name</b>	<b>No Neutral Dimmer and Motion Sensing Switch</b>	<b>No Neutral Dimmer Switch</b>	<b>No Neutral On/Off Button Switch</b>	<b>No Neutral On/Off Toggle Switch</b>	<b>No Neutral On/Off Paddle Switch</b>
<b>Description</b>	CSWDMBLBWF1NN	CSWDMOCBWF1NN	CSWONBLBWF1NN	CSWONBLTW1NN	CSWONBLPW1NN
<b>Switch Type</b>	Motion Dimmer	Basic Dimmer	Button Switch	Toggle Switch	Paddle Switch
<b>Capability</b>	On/Off, Dimming, Occupancy	On/Off, Dimming	On/Off	On/Off	On/Off
<b>Finish</b>	White	White	White	White	White
<b>Wattage (Output)</b>	120V, 60Hz: 150W LED 450W Halogen/ Incandescent	120V, 60Hz: 150W LED 450W Halogen/ Incandescent	120V, AC: Max 5A Incandescent Max 1.25A LED	120V, AC: Max 5A Incandescent Max 1.25A LED	120V, AC: Max 5A Incandescent Max 1.25A LED
<b>Minimum Wattage Requirement</b>	Minimum of 15W required. <b>Note:</b> Included bulb adaptor for medium base bulbs can be used if less than 15W.	Minimum of 15W required. <b>Note:</b> Included bulb adaptor for medium base bulbs can be used if less than 15W.	Minimum of 15W required. <b>Note:</b> Included bulb adaptor for medium base bulbs can be used if less than 15W.	Minimum of 15W required. <b>Note:</b> Included bulb adaptor for medium base bulbs can be used if less than 15W.	Minimum of 15W required. <b>Note:</b> Included bulb adaptor for medium base bulbs can be used if less than 15W.
<b>Switch Back Housing (LxWxH)</b>	2.6 x 1.75 x 1.18in (66 x 44.5 x 30mm)	2.6 x 1.75 x 1.18in (66 x 44.5 x 30mm)	2.6 x 1.75 x 1.18in (66 x 44.5 x 30mm)	2.6 x 1.75 x 1.18in (66 x 44.5 x 30mm)	2.6 x 1.75 x 1.18in (66 x 44.5 x 30mm)
<b>Overall Switch Unit (LxWxH)</b>	4.13 x 1.75 x 1.61in (105 x 44.5 x 41mm)	4.13 x 1.75 x 1.61in (105 x 44.5 x 41mm)	4.13 x 1.75 x 1.61in (105 x 44.5 x 41mm)	4.13 x 1.75 x 1.61in (105 x 44.5 x 41mm)	4.13 x 1.75 x 1.61in (105 x 44.5 x 41mm)
<b>Faceplate (LxWxH)</b>	4.6 x 2.9 x 0.28in (118 x 74 x 7mm)	4.6 x 2.9 x 0.28in (118 x 74 x 7mm)	4.6 x 2.9 x 0.28in (118 x 74 x 7mm)	4.6 x 2.9 x 0.28in (118 x 74 x 7mm)	4.6 x 2.9 x 0.28in (118 x 74 x 7mm)
<b>Weight</b>	0.25lbs (115g)	0.25lbs (115g)	0.25lbs (115g)	0.24lbs (110g)	0.24lbs (110g)
<b>Indicators</b>	Light Ring LED(RGBW)	Light Ring LED (RGBW)	Light Ring LED (RGBW)	LED (RGB)	LED (RGB)
<b>Buttons</b>	3	3	1 Central Button	1 Toggle Switch	1 Paddle Switch
<b>Occupancy Sensor</b>	PIR Sensor	No	No	No	No
<b>Ambient Light Sensor</b>	Yes	Yes	No	No	No
<b>Air Gap Switch</b>	Yes	Yes	No	No	No

## Electrical

<b>Input Voltage</b>	120V
<b>Wires</b>	3
<b>Wire Type</b>	Line, Load, Ground
<b>Neutral Required</b>	No
<b>Ground Required</b>	Yes

## Environmental

<b>Ambient Temperature</b>	32°F to 104°F (0°C to 40°C)
<b>Working Temperature</b>	32°F to 104°F (0°C to 40°C)
<b>Storage Temperature</b>	-4°F to 140°F (-20°C to 60°C)
<b>Relative Humidity</b>	< 88% 32°C
<b>Environment (Wet, Dry, Damp)</b>	Dry
<b>IP Rating</b>	IP20

## Controls

<b>On/Off Button</b>	Press or flip button to turn on/off the load (lights). This will not cut power to the switch.
<b>Dimmer +/- (Motion Dimmer and Dimmer Switch Only)</b>	Press '+' to turn up the brightness, press '-' to turn down the brightness. Brightness range: 5%-100%, 15% per step. Press and hold to dim the lights continually.
<b>Mobile Compatibility</b>	Works with iOS 13 and above and Android 9 and above

## Voice Assistant Compatibility

Works with Google Home and Amazon Alexa

## Wireless Standards

<b>Wireless</b>	Yes
<b>Wireless Protocol</b>	Wi-Fi (2.4 GHz) and BLE
<b>Local Control</b>	Local control with BLE
<b>Out-of-Home Control</b>	Out-of-Home Control via OTA (Over The Air)
<b>Wi-Fi Range</b>	30m (open area)

## Certifications

<b>Safety Listing</b>	UL1472 (Dimmer Switches) UL60730-1 (Switches)
<b>FCC</b>	FCC Part 15 Class B

## Reliability and Warranty

<b>Warranty</b>	2 Year Limited
<b>Warranty Operating Conditions</b>	<b>Voltage:</b> 120V/60hz <b>Temperature:</b> 32°F to 104°F (0°C to 40°C) <b>Relative Humidity:</b> < 88% 32°C

 The following information applies for all Cync No Neutral Switches unless otherwise noted.

## Box Contents



- (1) Faceplate
- (4) Wire Nuts
- (2) Screws (Paddle and Toggle Switches Only)
- (4) Screws (Dimmer + Motion Sensing Switch, Dimmer Switch, and Central Button Switch Only)
- (1) Bulb Adapter
- (1) Installation Guide
- (1) Quick Start Guide
- (1) Wire Label Sticker Set

\*Image shown above is the Cync No Neutral Required Dimmer and Motion Sensing Switch. Actual package will vary for each product.

## Compatibility

Cync switches will not work with traditional "non-smart" switches or 3-Way switches. Multi-location control is possible with two or more Cync Switches within a single App room via Bluetooth. For more information on wiring compatibility please view the [No Neutral Required Switch Compatibility & Wiring Configurations](#) article.