

# Cync Dimmer + Motion Sensing 3-Wire Smart Switch



## Smart Switch Specifications

Switch Function	On/Off/Dimming/Motion and Ambient Light Sensing
Style	Touch
Wall Plate Size	Standard
Power	120V, 60Hz
Power Capacity (LED)	Max 150W
Power Capacity (Incandescent/Halogen)	Max 450W
Neutral Required	No
Compatibility	LED/Incandescent/HID
Switch Back Housing	60 x 44.5 x 30 mm
Overall Switch Unit	105 x 44.5 x 41 mm
Faceplate	118 x 74 x 7 mm
Warranty	2 year limited warranty
Bluetooth	For local control
Wi-Fi	802.11 b/g/n @ 2.4 GHz
Mobile OS	iOS/Android via Cync App

## Smart Switch Includes:

- Dimmer + Motion Sensing Smart Switch
- Faceplate
- (4) Mounting Screws
- (4) Wire Nuts
- Wire Labels
- Installation Guide

## Wireless Home Control

Install smart bulbs in other fixtures and wirelessly control all your lights from the Smart Switch or from the Cync App.

## Makes Traditional Lights Smart

Turn ordinary bulbs into smart bulbs with enhanced functionality like out of home control, scheduling and setting scenes.

## Always Connected and Ready

The Smart Switch maintains voice and app control at all times, even when the wall switch is turned off.

## Built in Motion Detection

Motion and ambient light detection turn lights on or off based on the amount of natural light or motion in the room providing hands-free control and energy savings.

## Wirelessly Connect

Connect multiple switches without a travel wire required and connect switches on different circuits, like controlling a kitchen light from the hallway.

