

Cync Dimmer Smart 3-Wire Switch



Dimmer Smart Switch Specifications

| | |
|---------------------------------------|----------------------------------------------------------------------|
| Switch Function | On/Off/Dimming |
| Style | Touch |
| Wall Size | Standard |
| Power | 120V, 60Hz |
| Power Capacity (LED) | Max 150W |
| Power Capacity (Incandescent/Halogen) | Max 450W |
| Minimum Requirements | Wi-Fi connection, electrical box with neutral/ground/lead/load wires |
| Neutral Required | No |
| Switch Back House | 60 x 44.5 x 30 mm |
| Overall Switch Unit | 105 x 44.5 x 41 mm |
| Faceplate | 118 x 74 x 7 mm |
| Warranty | 2 year limited warranty |
| Bluetooth | For local control |
| Wi-Fi | 802.11 b/g/n @ 2.4 GHz |
| Mobile OS | iOS/Android via Cync App |

Dimmer Smart Switch Includes:

- Dimmer Smart Switch
- Wall Plate
- Installation Guide

Make Traditional Bulbs Smart

Turn ordinary bulbs into smart bulbs with enhanced functionality like out of home control, scheduling and setting scenes.

One Touch Wireless Room Control

Install with other Cync products and wirelessly controls all lights in the smart home from one smart switch.

Wireless 3-Way Switch Control

Control one light or group from multiple switches, such as controlling the kitchen lights from the hallway.

Customize Brightness Level

Dim and brighten traditional lights using touch or app and add voice control when paired with a voice assistant.

Schedules & Scenes

Lights connected to a Dimmer Smart Switch can be scheduled to turn on/off automatically. Scenes can be used with lighting and multiple other devices can be controlled together.

