

Cync Dimmer Smart 4-Wire Switch



Dimmer Smart Switch Specifications

Switch Function	On/Off/Dimming
Style	Touch
Wall Size	Standard
Power	120V, 60Hz
Power Capacity (LED)	Max 150W
Power Capacity (Incandescent/Halogen)	Max 450W
Minimum Requirements	Wi-Fi connection, electrical box with neutral/ground/lead/load wires
Neutral Required	Yes
Switch Back House	60 x 44.5 x 30 mm
Overall Switch Unit	105 x 44.5 x 41 mm
Faceplate	118 x 74 x 7 mm
Warranty	2 year limited warranty
Bluetooth	For local control
Wi-Fi	802.11 b/g/n @ 2.4 GHz
Mobile OS	iOS/Android via Cync App

Dimmer Smart Switch Includes:

Dimmer Smart Switch
Wall Plate

Make Traditional Bulbs Smart

Turn ordinary bulbs into smart bulbs with enhanced functionality like out of home control, scheduling and setting scenes.

One Touch Wireless Room Control

Install with other Cync products and wirelessly controls all lights in the smart home from one smart switch.

Wireless 3-Way Switch Control

Control one light or group from multiple switches, such as controlling the kitchen lights from the hallway.

Customize Brightness Level

Dim and brighten traditional lights using touch or app and add voice control when paired with a voice assistant.

Schedules & Scenes

Lights connected to a Dimmer Smart Switch can be scheduled to turn on/off automatically. Scenes can be used with lighting and multiple other devices can be controlled together.

